

# This is Why



- ▶ DIGITAL HD TV RECEIVER
- ▶ RECEIVE FREEVIEW HD SERVICES
- ▶ HDMI OUTPUT SUPPORTS HD RESOLUTIONS UP TO 1080P
- ▶ 1080P UPSCALING FOR SD PROGRAMS
- ▶ 8 DAY FREEVIEW TV GUIDE
- ▶ FRIENDLY USER INTERFACE FOR EASY OPERATION
- ▶ ETHERNET PORT FOR INTERACTIVE SERVICES AND FUTURE INTERNET-BASED SERVICES\*
- ▶ DOLBY DIGITAL PLUS VIA HDMI OR OPTICAL DIGITAL OUTPUT

Designed to receive Freeview HD services. DVB-T2/ DVB-T tuner supporting both HD and SD formats. Friendly user interface for easy operation. 8 day EPG. HDMI output supports HD resolutions up to 1080p. 1080p upscaling for SD programs. Dolby Digital Plus via HDMI or optical digital output. Ethernet port for interactive services and future internet-based services\*. USB port for software upgrade.

\*Services provided by the broadcaster through the DVB-T and DVB-T2 systems.

## TUNER

- DVB-T: ✓
- DVB-T2 (for HD broadcasts): ✓

## TECHNICAL

- Video - MPEG1: ✓
- Video - MPEG2: ✓
- Video - MPEG4: ✓
- Audio - MPEG1 layer I & layer II, MP3: ✓
- Audio - MPEG2 layer II, Dolby Digital: ✓
- Audio - MPEG2 AAC/AAC+: ✓
- SD Upscaling to HD: ✓
- HD output - 1080p / 1080i / 720p / 576p: ✓

## GENERAL CHARACTERISTICS

- Power requirement (AC): **220-240V**
- Maximum Power consumption (W): **7,5**
- Standby Low Power Consumption (W): **0,8**
- Physical dimensions (WxHxD in mm): **258x42x155**
- Weight (kg): **1,5**

## RECORDING

- Hard Disk capacity (GB): **n/a**
- USB port - S/W upgrade: ✓

## INTERFACES

- Audio R / L Connector: ✓
- Audio R / L Output: ✓
- Digital Audio Output: ✓
- Scart Sockets: ✓
- RGB Video Output: ✓
- RGB Video Input: ✓
- CVBS Video Output: ✓
- CVBS Video Input: ✓
- Analogue Audio Output: ✓
- Analogue Audio Input: ✓
- Digital Video Output: ✓
- HDMI: ✓
- Ethernet: ✓
- RF Input: ✓
- Loop-through Output: ✓
- Data Interface: **USB**

[www.sharp.co.uk](http://www.sharp.co.uk)

SHARP ELECTRONICS (UK) LIMITED  
4 FURZEGROUND WAY  
STOCKLEY PARK  
UXBRIDGE, MIDDLESEX UB11 1EZ. TEL. 0208 734 2000

**SHARP**